

2500W
SINGLE PHASE,230V-50Hz

OHV Overhead Valve Engine for Easy Operation and Mainetnance	Circuit Breaker Circuit Breaker Protects Generator in case of Overcurrent
OIL LEVEL PROTECTION Oil Level Indicator and Protection Avoid Engine Start in case of Low Level	VOLTMETER AC Output Voltage Level
AVR Automatic Voltage Regulator Keeps Voltage Level at 220V 1P and 380V 3P	CHOKE SYSTEM Rich Fuel Mixture in case of First or Cold Start by Restricting the Air Flow into the Engine,
DUAL ELEMENT AIR FILTER Dual-element air filter that purifies the sucked air from dust and dirt	FUEL LEVEL INDICATOR Shows remaining Fuel Level



PAAP3500

GENERAL SPECIFICATIONS

AC Nominal Power (kW)	2.5
Maximum Power (kW)	2.8
AC Nominal Current	10
Voltage (V)	230
Frequency (Hz)	50
Phase Number	1
Power Factor	0.8
Fuel Consumption (L/h)	1.1
Noise Level (dB(A))	76

MOTOR SPECIFICATIONS

Rpm	3000
Fuel Type	Gasoline
Oil Capacity (L.)	0.6
Fuel Tank Capacity (L.)	15
Start Type	Manuel
Cylindir	1
Cylindir Volume (mL)	196

WEIGHT and DIMENSIONS

Width (mm.)	605
Length (mm.)	490
Height (mm.)	490
Weight (kg.)	50
Power (kVA)	3.01-5
Start Type	Manuel
Fuel Type	Gasoline



PAAP3500 E (ELECTRICAL START)

GENERAL SPECIFICATIONS

AC Nominal Power (kW)	2.5
Maximum Power (kW)	2.8
ACNominal Current	10
Voltage (V)	230
Frequency (Hz)	50
Phase Number	1
Power Factor	0.8
Fuel Consumption (L/h)	1.1
Noise Level (dB(A))	76

MOTOR SPECIFICATIONS

Rpm	3000
Fuel Type	Gasoline
Oil Capacity (L.)	0.6
Fuel Tank Capacity (L.)	15
Start Type	ELECTRICAL
Cylindir	1
Cylindir Volume (mL)	196

WEIGHT and DIMENSIONS

Width (mm.)	605
Length (mm.)	490
Height (mm.)	490
Weight (kg.)	50
Power (kVA)	3.01-5
Start Type	ELECTRICAL
Fuel Type	Gasoline